



## Basic instructions of the Sporttraxx rally clock for Marshalls/Timekeepers

### Turn on clock

Press in sequence STOP - MENU - ENTER buttons

### Turn on GSM modem

Press the GSM button on top, GSM leds will blink

### Get Ready

Pressing Arrow UP button bring display to running rally time. Repeat if needed

### TC Time control

- Press the red STOP button only when competitor hands over the Time card
- Rally time on display will be stopped
- Type competitor's number using the keyboard
- If correct, confirm with ENTER button
- If wrong, overwrite number then press ENTER button
- Using Arrow UP button bring display back to running rally time

### SS Start with beams

- Line up competitor in front of beam line respecting the imposed distance
- Do not walk through/hit the beams
- Make sure that, using the Arrow up button, the display shows the running rally time
- Advice the competitor to get ready and to focus on the starting light
- As soon as the competitor has started and crossed the beam, the time will be stopped.
- Type competitor number using the keyboard
- If correct, confirm with ENTER button
- If wrong, overwrite number then press ENTER button
- Using Arrow UP button bring display back to running rally time

### SS Start manual countdown

- Line up competitor in front of beam line respecting the imposed distance
- Make sure that, using the Arrow up button, the display shows the running rally time
- Run the manual countdown
- Press the STOP button only AFTER the competitor has started. Time will be stopped
- Type competitor number using the keyboard
- If correct, confirm with ENTER button
- If wrong, overwrite number then press ENTER button
- Using Arrow UP button bring display back to running rally time

### FF with beams

- Always make sure the rally time is kept running on the display using the Arrow Up button
- When competitor passes on the beam, display will be stopped
- Type competitor number using the keyboard
- If correct, confirm with ENTER button
- If wrong, overwrite number then press ENTER button
- Using Arrow UP button bring display back to running rally time
- If the clock has collected more times (mainly due to dust) press Arrow Up button several times

## FF without beams

- Always make sure the rally time is kept running on the display using the Arrow Up button
- When the competitor passes on the finish line, press the STOP button
- Type competitor number using the keyboard
- If correct, confirm with ENTER button
- If wrong, overwrite number then press ENTER button
- Using Arrow UP button bring display back to running rally time

## Connection test

After stopping the clock (using STOP button or beam), if using the competitor's number 9999 and confirming with the ENTER button, the TEST led will light on shortly to confirm the correct connection of the modem.

## Beam button/led

If the Beam button is pressed and as long as the Beam Led is on, the beam will not stop the clock. Press again to switch off this function. Do not forget this function on when race is running.

## MODEM RESET function

Only if requested from race control, press and hold for 10 seconds the GSM button. That will reset and turn off the modem. Modem needs to be restarted by pressing again shortly the same button.

